

**Volt Stick**  
Non-contact Testers



## Volt Stick SOUND

The original and still the best, Volt Stick is an instant tester for safely checking the presence of an AC voltage, without making any disconnections in cables, wall sockets, fuses, circuit breakers, junction boxes, etc. No current flow is needed for correct operation.

The red indicator in the tip will illuminate on detection of AC voltage simply by applying the tip close to any connection point, or moving it along any insulated cable.

The Volt Stick SOUND features a detection buzzer for even greater clarification. Also ideal for 'detection round corners', in bright daylight and in awkward out of sight areas. High visibility green tube for ease of identification if dropped or hidden in the toolbox.

### Features:

- Added 'Beeper' feature
- Locates breaks in cables
- Detects blown fuses inside plugs or fuse holders
- Distinguishes between live and neutral wires in both single and three-phase supplies
- Identifies voltage-carrying cables in junction boxes
- Identifies faulty in-line switches
- Locates defective in-series light bulbs



### Specifications:

Model:	Volt Stick SOUND
Voltage Range	220 ~ 230v AC
Sensitivity	Functions @ 4mm distance from 2.5mm <sup>2</sup> conductor carrying 220v AC
Response Time	Immediate
Intrinsically Safe	No
Power Requirements	2 x AAA (LR03) batteries (supplied)
Relative Humidity	80% @ 30°C, 50% @ 40°C
Operating Temp	-10° ~ +50°C
Overvoltage	CAT III 1000v AC
Dimensions	145(L) x 18(Ø) mm
Weight	40g (including batteries)

All models are fully approved to IEC 61010-1, CAT111 1000v AC and CE. Are yours?!!